
# lucent

## EasyFit Trim Round Wallwash



3.78" (96mm) overall diameter. Range of soft appearance with minimal trim for achieving trimless effect. Fixed and Adjustable version available.

Supplied with a remote driver box and a plug and play tethered power supply. Also for mounting to T-Bar on grid ceilings.



LED Source	LED51/2	LED51/U
CCT	3000K	3000K
Drive Current	350mA	350mA
Power inc Driver	13.6W	13.6W
Beam Angle	38°	38°
Delivered Lumens	718	590
Delivered Intensisty cd	927	800
Efficacy Im/w	53	43
Forward Volt	33V	33V
CRI	≥90 CRI	≥98 CRI

Ceiling void minimum depth: Driver box A - 11.00" (280mm) / Driver box B - 14.96" (380mm)



Projec	ct Ref:				Location Ref:									
Specif	y fixture part nu	mber (	All boxes	s must b	oe filled	in to corre	ectly order)							
A960-L	.ED-WW						38	ALEZ						
Finish —														
WH	White													
BK	Black													
RAL	Custom*													
Location														
XX	Dry													
DP WT	Damp Wet													
	hickness —													
SC SC	Standard Ceiling (1/2"-5/				•									
C	Custom	0, 1,												
LED Type														
LED51/2	LED51/2 (90CRI)													
LED51/U	LED51/U (98CRI - Not a	vailable wit	h 4000K)											
CCT —							_							
27	2700K													
30 35	3000K 3500K													
40	4000K (90 CRI ONLY)													
Beam An														
38	38													
EasyFit														
ALEZ	Lucent EasyFit													
Supply Vo	oltage ———								_					
120	120V													
277	277V													
Dimming	Protocol —													
S	Non-Dimmable (Driver E	30x A - 9.75	")											
Р	TRIAC/Phase (120V ON	, ,	,											
LPE	Lutron Hi-Lume Premier		ystem (Driver	Box A - 9.75'	")									
A ESD	0-10V (Driver Box A - 9.7 EldoLED Solo DALI (0.19	*	(Driver Pay P	13.70"										
EED	EldoLED Eco DALI (1% [	0,	*	,										
ESA	EldoLED Solo 0-10V (0.1)													
EEA	EldoLED Eco 0-10V (1%	0	· ·	,										
Louvre/L														
XX	Not required													
LL45 LLCC	Honeycomb Warm Tone													
LLUV	UV													

NIC - No contact with insulation


Ceiling void minimum depth: Driver box A - 11.00" (280mm) / Driver box B - 14.96" (380mm)


Issued: 03/23




### **Driver Boxes**


## Driver Box A





## Driver Box B









#### Technical Details

\*Custom RAL code must be specified. Custom RAL colours can increase prices and lead times

Dimming. Whilst Lucent can offer the majority of its luminaires with various dimming options, it remains the responsibility of the specifier/installer to check and ensure compatibility of any control equipment used. Additional cabling may be required depending on the dimming protocol specified.

^ Depth indicated is the minimum recess depth for the luminaire with a remote mounted LED driver. Installing a driver through either the luminaire cut-out or installation kit may require additional recess depth, please refer to the relevant luminaire installation instructions for further details. Data correct at time of publishing

First Fix Requirement. Luminaire comprised of fixture body with ceiling trim and installation kit, which is to be fitted into the ceiling once finished. Ensure correct alignment of the installation kit before final assembly (see luminaire instillation instructions for details)

Location. Tested from underside of the ceiling

It is the policy of Lucent Lighting to continually review and improve its products and therefore reserve the right to change any details of product or withdraw specifications without prior notice.

This specification sheet supersededs all previous versions.

All intellectual property rights pertaining to the product described above and to this document are owned by or licensed to Lucent Lighting Ltd.

We reserve the right to take whatever action is necessary to protect those intellectual property rights.

Please notify Lucent Lighting Ltd of any inaccuracies immediately. E&OE



Issued: 03/23

## lucent<sub>®</sub>

Light efficiency:


53 Lumen/Watt

**Light quality:** 

CRI: 89.9

Color temperature:

3000 K



Product name:

Trim Round Wallwash -LED50 ONE GEN2, 3000K, 38°, 350mA


Item number:


A960-WW -


LED51/2-30-38-350mA

Delivered information for above fixture and LED combination.

Output: 718 Lumen Peak intensity: 927 cd Power consumption: 13.6








Color temperature	Color rendering index	Red component	Color fidelity	Color gamut	Color quality scale	Color coordinate cie 1931	Color coordinate cie 1931	Color coordinate	Color coordinate	Color diviation from black body
ССТ	CRI	CRI R9	TM30 Rf	TM30 Rg	cqs	х	у	u	٧	Δuv
3000 K	89.9	50.3	89.8	98.5	89.3	0.437	0.404	0.249	0.350	0.0029

#### Beam details



#### Beam angels

Beam angle 50%	Field angle 10%	Cutoff angle 2,5%				
50.1°	96.4°	130.9°				

#### Beam intensities

Peak intensity	Int. ratio in 120° cone	Int. ratio in 90° cone
927 cd	94.9%	75.8%

## Beam intensities from 1-20m

1m	2m	3m	4m	5m	6m	7m	8m	9m	10m	11m	12m	13m	14m	15m	16m	17m	18m	19m	20m
3.3ft	6.6ft	9.8ft	13.1ft	16.4ft	19.7ft	23ft	26.2ft	29.5ft	32.8ft	36.1ft	39.4ft	42.7ft	45.9ft	49.2ft	52.5ft	55.8ft	59.1ft	62.3ft	65.6ft
297lx	74lx	33lx	19lx	12lx	8lx	6lx	5lx	4lx	3lx	2lx	2lx	2lx	2lx	1lx	1lx	1lx	1lx	1lx	1lx
27.6fcd	6.9fcd	3.1fcd	1.7fcd	1.1fcd	0.8fcd	0.6fcd	0.4fcd	0.3fcd	0.3fcd	0.2fcd	0.2fcd	0.2fcd	0.1fcd						

The above information is for 3000K colour temperature, for specific module information please see LED spec located on our website

For information regarding other colour temperatures please use the following factors for lumen output and candelas:

2700K = 1 4000K = 1.084






43 Lumen/Watt

Light quality:

CRI: 97.8

Color temperature:

3000 K



Product name:

A960-LED-WW -LED51\_U-30-38-350mA

Item number:


Trim Round Wallwash - LED51\_U-30-38-350mA


Delivered information for above fixture and LED combination.


Output: 590 Lumen

Peak intensity: 800 cd

Power consumption: 13.6








Color temperature	Color rendering index	Red component	Color fidelity	Color gamut	Color quality scale	Color coordinate cie 1931	Color coordinate cie 1931	Color coordinate	Color coordinate	Color diviation from black body	
ССТ	CRI	CRI R9	TM30 Rf	TM30 Rg	cqs	х	у	u	٧	Δuv	
3000 K	97.8	86.8	93.4	98.1	94.7	0.437	0.404	0.248	0.348	0.0016	

#### Beam details



#### Beam angels

Beam angle 50%	Field angle 10%	Cutoff angle 2,5%				
49.4°	105.2°	140.4°				

#### Beam intensities

Peak intensity	Int. ratio in 120° cone	Int. ratio in 90° cone				
800 cd	93.6%	73.6%				

#### Beam intensities from 1-20m

1m	2m	3m	4m	5m	6m	7m	8m	9m	10m	11m	12m	13m	14m	15m	16m	17m	18m	19m	20m
3.3ft	6.6ft	9.8ft	13.1ft	16.4ft	19.7ft	23ft	26.2ft	29.5ft	32.8ft	36.1ft	39.4ft	42.7ft	45.9ft	49.2ft	52.5ft	55.8ft	59.1ft	62.3ft	65.6ft
229lx	57lx	25lx	14lx	9lx	6lx	5lx	4lx	3lx	2lx	2lx	2lx	1lx							
21.3fcd	5.3fcd	2.4fcd	1.3fcd	0.9fcd	0.6fcd	0.4fcd	0.3fcd	0.3fcd	0.2fcd	0.2fcd	0.1fcd								

The above information is for 3000K colour temperature, for specific module information please see LED spec located on our website

For information regarding other colour temperatures please use the following factors for lumen output and candelas:

2700K = 1