lucent




Mix85 Edge Accent Trimless Part L Compliant Downlight

TM65.2 6kgCO2e


TM66 2.5 CEAM




Ø85mm (3.35") overall trim. Ø45mm (1.77") aperture. Available with standard trim kit or plaster-in kit for flush appearance. Family of matching products also available.



Mix85 Edge with Trimless Kit TL1 ⁽¹⁾ (front fitting, full skim) Cut-out Ø90mm Required depth height + 25mm.



Mix85 Edge with Trimless Kit TL2 ⁽¹⁾ (rear fitting, partial skim) Cut-out Ø90mm Required depth height + 25mm.



Mix85 Edge with Trimless Kit TL3 ⁽¹⁾ (rear fitting, solid ceiling) Cut-out Ø86mm Required depth height + 25mm.

Issued: 10/24

LED Source	LED51/Q-HE	LED51/Q-HE	LED51/Q-HE	LED51/Q-HE	
CCT	3000K	3000K	3000K	3000K	
Drive Current	200mA	200mA	200mA	200mA	≥75 Dwellin Complia
Power inc Driver	8.0W	8.0W	8.0W	8.0W	
Beam Angle	NF (16°)	MF (20°)	FL (31°)	WFL (41°)	1
Delivered Lumens	688	923	851	645	
Delivered Intensisty cd	5932	5961	3000	1334	≥95 Ger Compli
Delivered Lumens per circuit watt	86	115	106	80	_
Forward Volt	33V	33V	33V	33V	1 '
CRI	≥95 CRI	≥95 CRI	≥95 CRI	≥95 CRI	≥80 Dis Compl

Apply these factors to 3000 K for lumen output of other CCTs: $2700 \text{K} \times 0.98 / 4000 \text{K} \times 1.02$.



Project Ref:				Location Re	ef:			
Fixture Ord	er Code:	MX85010-ED				- 0		
Fixture MX85010-ED	Mix85 Edge A	ccent for LED						
Installation (1) TL1 TL2 TL3 TL4 (2) TL5 (2)	Trimless for Full Skim Trimless for Partial Skim ceilings (12-15mm total thickness) Trimless for Solid Ceilings (12-15mm total thickness) Trimless for Partial Skim ceilings (25-28mm total thickness) Trimless for Solid Ceilings (25-28mm total thickness)							
Finish								
WH02 BK02 RL99* ABR1 ABZ1 PCH1 PNK1 PBR1	White RAL 90 Black RAL 90 Custom RAL 0 Antique Brass Antique Bronz Polished Chro Polished Nick Polished Brass	05 Colour* ze ome el						
IP Rating 54 65	IP54 IP65	TI 1 Trian		TI 2 Trimber	City programme and in the control of	TI 3 Trivolege Vita gali	el acilina	
(1) For any ceiling (2) Adjustment m	thickness or c ay be limited i	onstruction type on thicker ceiling co	not shown ple	ease contact Lu	icent	TL3 Trimless Kit, solins for details.		
LED Order	Code:	LED51/Q-HE				_ T		
LED LED51/Q-HE CCT	LED50 ONE (QUANTUM High Et	ficacy					
CCT 27 30 40 (3)	90 CRI 2700k 90 CRI 3000k 90 CRI 4000l	<						
Beam NF MF FL WFL	Narrow Flood Medium Flood Flood Wide Flood	d						
(3) contact Lucer	nt for availabilit	Ty						
Driver Option	ons:							
S A P D B	Non-Dim Analogue (0-1) Phase DALI Bluetooth**	Ov)						
Emergency	Options:							
Emergency E ED ES	Maintained 3h Maintained 3h Maintained 3h	nr Emergency nr DALI Self Test nr Self Test						

Issued: 11/24



Finish selection



Antique Brass



Antique Bronze



Polished Brass



Polished Nickel



Polished Chrome

Accessories



Honeycomb Louvre



Diffusing Lens



Frosted Lens



Heavy Spread Lens



Linear Spread Lens

Accessories Order Code:



LL45 Honeycomb Louvre
LLDF Diffusing Lens
LLFR Frosted Lens
LLLS Linear Spread Lens
LLHS Heavy Spread Lens

Issued: 11/24



Technical Details

*Custom RAL code must be specified. Custom RAL colours can increase prices and lead times

Dimming. Whilst Lucent can offer the majority of its luminaires with various dimming options, it remains the responsibility of the specifier/installer to check and ensure compatibility of any control equipment used. Additional cabling may be required depending on the dimming protocol specified.

**Bluetooth (wireless) is the communication method. The exact dimming protocol must be confirmed to allow the selection of suitable drivers or bluetooth devices.

^ Depth indicated is the minimum recess depth for the luminaire with a remote mounted LED driver. Installing a driver through either the luminaire cut-out or installation kit may require additional recess depth, please refer to the relevant luminaire installation instructions for further details. Data correct at time of publishing

First Fix Requirement. Luminaire comprised of fixture body with ceiling trim and installation kit, which is to be fitted into the ceiling once finished. Ensure correct alignment of the installation kit before final assembly (see luminaire instllation instructions for details)

IP Rating. Tested from underside of the ceiling

Note that the picture of the finishes provided is for illustrative purposes only. The finishes may vary in colour, texture and appearance. Contact Lucent lighting Ltd for more information.

It is the policy of Lucent Lighting to continually review and improve its products and therefore reserve the right to change any details of product or withdraw specifications without prior notice.

Luminaires designed to comply with EN60598 and all other standards.

This specification sheet supersededs all previous versions.

All intellectual property rights pertaining to the product described above and to this document are owned by or licensed to Lucent Lighting Ltd.

We reserve the right to take whatever action is necessary to protect those intellectual property rights.

Please notify Lucent Lighting Ltd of any inaccuracies immediately. E&OE

Issued: 11/24